
## ROCKER SWITCH ACCESSORY



UTV PARTS AND ACCESSORIES
SCOOTER PARTS AND ACCESSORIES
TIRES AND WHEELS
ELECTRICAL COMPONENTS
PERFORMANCE PARTS
MOTORCYCLE PARTS AND ACCESSORIES
LED LIGHT BARS
BUMPERS DOORS ROOFS
SAFETY GEAR
CNC ACCESSORIES



STV Motorsports® Laser Re... 20A 12V On/off LED Light New

WWW.STVMOTORSPORTS.COM

WWW.STVMOTORSPORTS.COM


### WARNING!!!

Do not reverse the (+) terminals with (-) on the switch. Damage to led bulb will occur and warranty will be void!!!

Please read carefully the instructions before installing the switch. Do not exceed 20A load on the switch.

For more information or support contact us at support@stvmotorsports.com or (702) 701-7101

#### **ON-OFF 3 PINS**




Connect #7 (-) to a ground

Connect #2 (+) from your source with inline fuse Connect #3 to your relay or acc. (application)

#### **ON-OFF 5 PINS**

Connect #8 (-) to a ground for upper light
Connect #7 (+) to a ground for lower light can be jumpered from #8
Connect #2 (+) from your source with inline fuse



Connect #3 to your relay or acc. (application)
Connect #6 to your dash light circuit or Ignition
to be on when your dash light are on or when you
turn on the ignition (this is lower light)

# ON-ON-OFF 6 PINS | Lighting | Lighting| | Lighting|

Connect #7 (-) to a ground Connect #2 (+) from your source with inline fuse Connect #3 to your relay or acc.

Connect #3 to your relay or acc (first application)

Connect #5 (+) from your source with inline fuse Connect #6 to your relay or acc. (second application)

Connect #8 to your dash light circuit or ignition to be on when your dash light are on or when you turn on the ignition (this is lower light)

#### ON-OFF-ON 7 PINS

Connect #7 (-) to a ground Connect #2 (+) from your source with inline fuse Connect #3 to your relay or acc.

(push down application)
Connet #1 to your relay or acc.
(push up application)

Connect #5 (+) from your source with inline fuse
Connect #6 to your relay or acc. (push down second application)
Connect #4 to your relay or acc. (push up second application)